


LED Multi Konverter mit Dimmfunktion

dimmbar mit 1-10V und Taster, Master- / Slave steuerbar

• Ausgangsstrom bzw. -spannung kann über Dip-Schalter voreingestellt werden.

	32W 250...900mA	Konstantstrom 13W 15...53V 250mA 16W 15...53V 300mA 18W 10...53V 350mA 21W 10...53V 400mA 23W 5...52V 450mA 25W 2...50V 500mA 27W 2...50V 550mA 30W 2...50V 600mA 32W 2...49V 650mA 32W 2...46V 700mA 20W 2...43V 750mA 20W 2...40V 800mA 20W 2...39V 850mA 20W 2...37V 900mA	Konstantspannung 11W 12V max. 900mA 20W 24V max. 830mA	TCI-125421
---	--------------------	---	--	------------

	60W 350...1050mA	Konstantstrom 25W 2...74V 350mA 35W 2...72V 500mA 39W 2...72V 550mA 46W 2...72V 650mA 50W 2...72V 700mA 54W 2...72V 750mA 60W 2...70V 850mA 60W 2...66V 900mA 60W 2...60V 1000mA 60W 2...57V 1050mA	Konstantspannung k.A.	TCI-127411
---	---------------------	---	-----------------------	------------

	20W 250...700mA	Konstantstrom 12W 15...49V 250mA 17W 10...49V 350mA 19W 5...49V 400mA 20W 5...45V 450mA 20W 5...40V 500mA 20W 3...36V 550mA 20W 3...33V 600mA 20W 3...28V 700mA	Konstantspannung 16W 24V max. 700mA	TCI-125403
--	--------------------	---	--	------------

	60W 350...1050mA	Konstantstrom 25W 2...74V 350mA 35W 2...72V 500mA 39W 2...72V 550mA 46W 2...72V 650mA 50W 2...72V 700mA 54W 2...72V 750mA 60W 2...70V 850mA 60W 2...66V 900mA 60W 2...60V 1000mA 60W 2...57V 1050mA	Konstantspannung k.A.	TCI-127413
--	---------------------	---	-----------------------	------------

L x B x H	10,3 x 6,7 x 2,1 cm 12,4 x 7,9 x 2,2 cm 11 x 5,2 x 2,2 cm 12,4 x 7,9 x 2,2 cm
-----------	--

Farbe	weiß
-------	------